

Return loss (dB)	VSWR	Voltage Reflection Coefficient
1	17.39	0.891
2	8.72	0.794
3	5.85	0.708
4	4.42	0.631
5	3.57	0.562
6	3.01	0.501
7	2.62	0.447
8	2.32	0.398
9	2.10	0.355
10	1.93	0.316
11	1.79	0.282
12	1.67	0.251
13	1.58	0.224
14	1.50	0.200
15	1.43	0.178
16	1.38	0.158
17	1.33	0.141
18	1.29	0.126
19	1.25	0.112
20	1.22	0.100
21	1.20	0.089
22	1.17	0.079
23	1.15	0.071
24	1.14	0.063
25	1.12	0.056
26	1.11	0.050
27	1.09	0.045
28	1.08	0.040
29	1.07	0.035
30	1.07	0.032
infinite	1.00	0.000